



**Europäisches
Patentamt**

**European
Patent Office**

**Office européen
des brevets**

Bescheinigung

Certificate

Attestation



Die angehefteten Unterla-
gen stimmen mit der
ursprünglich eingereichten
Fassung der auf dem näch-
sten Blatt bezeichneten
europäischen Patentanmel-
dung überein.

The attached documents
are exact copies of the
European patent application
described on the following
page, as originally filed.

Les documents fixés à
cette attestation sont
conformes à la version
initialement déposée de
la demande de brevet
européen spécifiée à la
page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

00300254.0

Der Präsident des Europäischen Patentamts;
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

I.L.C. HATTEN-HECKMAN

DEN HAAG, DEN
THE HAGUE, 13/11/00
LA HAYE, LE

This Page Blank (uspto)



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets

Blatt 2 der Bescheinigung
Sheet 2 of the certificate
Page 2 de l'attestation

Anmeldung Nr.:
Application no.: 00300254.0
Demande n°:

Anmeldetag:
Date of filing: 14/01/00
Date de dépôt:

Anmelder:
Applicant(s):
Demandeur(s):
LUCENT TECHNOLOGIES INC.
Murray Hill, New Jersey 07974-0636
UNITED STATES OF AMERICA

Bezeichnung der Erfindung:
Title of the invention:
Titre de l'invention:
Method and rake receiver for code-tracking in CDMA communication systems

In Anspruch genommene Priorität(en) / Priority(ies) claimed / Priorité(s) revendiquée(s)

Staat:
State:
Pays:

Tag:
Date:
Date:

Aktenzeichen:
File no.
Numéro de dépôt:

Internationale Patentklassifikation:
International Patent classification:
Classification internationale des brevets:
H04B1/707

Am Anmeldetag benannte Vertragsstaaten:
Contracting states designated at date of filing: AT/BE/CH/CY/DE/DK/ES/FI/FR/GB/GR/IE/IT/LI/LU/MC/NL/PT/SE/TR
Etats contractants désignés lors du dépôt:

Bemerkungen:
Remarks:
Remarques:

See for original title of the application page 1 of the description

This Page Blank (uspto)

99LUC1570EPP

Lucent Technologies

Method and Rake Receiver for Code-Tracking in Communication SystemsDescription

5

Field of the Invention

The invention relates to a method and a rake receiver for code-tracking in communication systems in general and in code division multiple access (CDMA) communication systems being subject to multipath fading in particular.

Prior Art

Digital wireless communication systems are of increasing interest for all types of data and speech transmission. A frequently used method in particular for mobile cellular communications is code division multiple access (CDMA). For CDMA the signal to be transmitted is typically spread to a multiple of its original bandwidth. The signal with spread bandwidth is less sensitive to interference and the spectral power density is reduced. Commonly, direct sequence CDMA is used, where the signal is multiplied or correlated by a code sequence before modulation. The spread and correlated symbols are called chips. Using a plurality of code sequences being orthogonal to each other a plurality of communication connections can utilise the same frequency band. Due to the orthogonality of the codes the transmitted signals can be decoded or decorrelated uniquely in the receiver. An advantageous group of code sequences are so-called pseudo-noise (PN) bit sequences which are typically used for direct

sequence CDMA. CDMA and pseudo-noise correlation are known to those skilled in the art.

5 However, in a wireless communication system a transmitted signal may still propagate along different paths due to reflection or scattering. Therefore, the signal is received as a superposition of different signal components each propagated along one of the possible paths. As reflected signals will be differently delayed according to their paths
10 compared to each other and compared to the direct signal, each of the signal components of one specific path is interfered by a plurality of other time- and phase-shifted signal components of other paths. If there is no direct sight between the transmitter and the receiver the connection can
15 still be provided by the reflected or scattered signal components, but their interference generally causes disadvantageous effects to the connection performance. Phase-shifted signal components reduce the signal-to-noise ratio of the direct or main signal component and cause power
20 dissipation. Furthermore, the superposition of phase-shifted signals may cause destructive interference between different signal components. These disadvantageous effects reduce the reliability and stability of the decorrelation in the receiver, e.g. increase the bit error rate. Especially when
25 one of the communication partners, e.g. a mobile terminal or phone, is moving these multipath phase shift and interference may change quickly causing a fast fading effect.

30 To reduce interference of phase shifted signal components several algorithms have been proposed in the past for tracking of the multipath delays. All of them suffer from either high sensitivity to multipath fading and thus reduced

performance in such environments, or implementation complexity which is prohibitive for the use in mobile terminals, where size, production cost and power consumption are critical issues. One example for code-tracking is the so-called early-late gate timing error detector (EL-TED), being a natural solution to a mathematical optimisation problem for nondispersive, additive white gaussian noise channels (AWGN). For a detailed description of prior art see Heinrich Meyr, Marc Moeneclaey and Stefan Fechtel, Digital Communication Receivers: Synchronization, Channel Estimation and Signal Processing, John Wiley and Sons, New York, 1998, Heinrich Meyr and Gerd Ascheid, Synchronization in Digital Communications. Vol. 1, John Wiley & Sons, New York, 1990 and A.J. Viterbi, CDMA - Principles of Spread Spectrum Communication, Addison-Wesley Publishing Company, Reading (MA), 1995.

The EL-TED is able to track echo path delays, as long as the relative delay between two paths is larger than some threshold. If the relative delay is smaller than the threshold, the EL-TED can no longer distinguish the two paths. Furthermore, tracking of weaker paths (lower power) can be disturbed by stronger paths with a relative delay larger than the aforementioned threshold. For an example of an algorithm with significantly higher implementation complexity than the EL-TED, see R.A. Iltis, An EKF-Based Joint Estimator for Interference, Multipath, and Code Delay in a DS Spread-Spectrum Receiver, IEEE Transactions on Communications, Vol. 42, No. 2/3/4, February-April 1994.

In indoor mobile communication scenarios, the path delay of the last identifiable echo path is small compared to outdoor

scenarios. All of the signal energy is dispersed around the path with the shortest delay and a sufficient echo path resolution is critical for adequate receiver performance, expressed for instance as the bit-error rate (BER). None of the existing EL-TED algorithms with reasonable complexity is able to track adjacent path delays which are separated by less than the mentioned threshold. With such a tracking system, the required signal-to-noise ratio to achieve a certain BER is reduced significantly.

10

A system using multipath interference cancellation in the code-tracking loop was presented by Wern-Ho Sheen and Chien-Hsiang Tai, A Noncoherent Tracking Loop With Diversity and Multipath Interference Cancellation for Direct-Sequence Spread-Spectrum Systems, IEEE Transactions on Communications, Vol. 46, No. 11, November 1998. There, a group of rake fingers is tracked jointly. In each finger, resampling and recoding is performed after the normal rake correlation in order to yield signals which model the interference for each multipath. These interference terms can then be subtracted from the incoming signal in order to improve the tracking performance, inherently by allowing a finger assignment where adjacent fingers are placed around one chip duration apart. This scheme suffers from high implementation complexity, expressed by the resampling and recoding necessary in each finger.

Therefore, it is an object of the present invention to provide a method and/or a rake receiver for code-tracking in CDMA communication systems of low complexity and cost.

Another object is to provide a method and/or rake receiver

with stable and reliable code-tracking as well as improved performance, reducing the disadvantages of the prior art.

Surprisingly simple, these objects of the invention are
5 already achieved by the method according to claim 1 and the rake receiver according to claim 16.

According to the present invention an electromagnetic signal of a CDMA communication system is received. The received
10 signal is generated from the transmitted signal by a superposition of signal components of different signal paths. The transmitted signal is preferably spread and coded by a pseudo-noise bit sequence. In particular, different signal paths are created by scattering, diffraction and/or
15 reflection of the signal. Therefore, the signal components may be time- and phase-shifted to each other and having different amplitudes.

The received signal is preferably filtered and digitised by
20 an analog-to-digital (A/D) converter. The digitised signal is distributed or conveyed to a plurality (N) of receiver fingers which are constituents of a so-called rake receiver.

Furthermore, the digitised signal is distributed or conveyed
25 to a detection and a synchronising streams or branches, preferably in each of the receiver fingers. The signal is preferably distributed by a digital interpolator/decimator.

In the detection and synchronisation streams the signal is
30 preferably correlated with the complex-conjugate of the pseudo-noise bit sequence used in the transmitter. The decorrelated signal in the synchronisation stream is

multiplied with reconstructed transmitted symbols.

The method further comprises a step of reducing interference of at least one signal component of signal path j with the
5 signal component of signal path i by an interference reduction device of a receiver finger which is assigned to signal path i , where $i \neq j$.

Preferably reducing of interference comprises a subtraction
10 of an interference signal from the decorrelated digitised signal. The interference signal is preferably calculated using the complex weight coefficients of at least one or all signal paths j ($j \neq i$). Preferably the subtraction takes place on symbol rate $1/T$. Preferably, interference reduction
15 is provided in each rake finger. Advantageously, interference reduction provides a stable and reliable code-tracking of low complexity and cost. Furthermore, the method and device according to the invention yield an improved estimation of the timing delay τ .

20

In a preferred embodiment of the invention the decorrelation by the pseudo-noise sequence takes place in a timing error detector which includes a first and second correlators. The digitised signal is transmitted to the first correlator and
25 the time-shifted signal is transmitted to the second correlator. The signals are correlated, preferably multiplied with the complex-conjugate of the pseudo-noise sequence in the first and second correlator, respectively, and the two resulting output signals are subtracted. The decorrelated
30 signal is preferably multiplied with reconstructed transmitted symbols.

In a further embodiment the real part of the complex output signal of the interference reduction device is filtered. The output signal of the filter provides an estimated time delay $\hat{\tau}^{(i)}$ for the signal component of the respective signal path i .

5

The invention is described in detail hereinafter by means of preferred embodiments and reference is made to the attached drawings.

10 Brief description of the Figures

It is shown in

Fig. 1 a block diagram of a rake receiver with N receiver fingers.

15 Fig. 2 a block diagram of a receiver finger i of a rake receiver with a conventional coherent early-late timing error detector,

Fig. 3 a block diagram of a receiver finger i of the rake receiver of Fig. 1 with an early-late timing error detector according to a first embodiment of the invention,

20

Fig. 4 a diagram of the detector characteristic of a conventional coherent early-late timing error detector,

25 Fig. 5 a diagram of the detector characteristic of a conventional coherent early-late timing error detector for two signal components i and j ,

Fig. 6 a block diagram of a receiver finger i of a rake receiver according to a second embodiment of the invention and

30 Fig. 7 a block diagram of a receiver finger i of a rake receiver according to a third embodiment of the invention.

Detailed Description of the Invention

The block diagrams of Fig. 1, 3, 5 and 6 can also be read as flow charts of the method according to the invention. Same or equivalent items of the conventional timing error detector 102' shown in Fig. 2 and of the timing error detector 102 according to the present invention are denoted by the same numerals.

Fig. 1 presents the general structure of code-tracking loops for a plurality of receiver fingers 1, 2, ..., N of a rake receiver 17 for a direct sequence CDMA communication system. For direct sequence CDMA the signal is spread by a factor of 2^L in the transmitter and multiplied by a code sequence before modulation, yielding chips of a duration T_c . For the preferred embodiment quadrature phase shift keying (QPSK) and a pseudo-noise (PN) code sequence 112 are used. Also binary phase shift keying (BPSK) or any other linear modulation scheme can be applied.

A digital spread spectrum rake receiver 17 including a digital interpolator/decimator 16 is shown in Fig. 1. A wirelessly transmitted signal 10 is received by the device 100 and is fed through a pulse matched filter 12. The filter 12 is a root raised-cosine pulse filter, matched to the transmission filter (not shown) which is also of root raised-cosine shape in the transmitter (not shown). As best seen in Fig. 2 and 3, an analog-to-digital (A/D) converter 14 generates samples $z(t = n \cdot T_s)$ of the pulsed matched-filtered signal 13 at equidistant times t which are integer multiples n of the sample time T_s and feeds them to the digital interpolator/decimator 16. The digital

interpolator/decimator 16 generates intermediate samples $z(t = k \cdot T_c + \hat{\tau})$ 110 of the same signal at equidistant times t which are integer multiples k of the chip duration T_c shifted by estimated timing instants $\hat{\tau}$ for each of the N identical
5 rake fingers. The signal is sampled at a rate which is higher than the chip rate, typical oversampling factors are in the range of four to eight. The digital interpolator/decimator 16 interpolates between the samples, as sampling rate $1/T_s$ and chip rate $1/T_c$ can be different, and performs a sampling rate
10 conversion from the sampling rate to the chip rate.

The interpolated signal 110 is fed to the detection stream or branch, where a correlation of the signal 110 with the complex-conjugate pseudo-noise (PN) code 112 in each of the N
15 fingers takes place. In the detection stream path delay and phase shift of each signal component is equalised and the signal amplitude is optimised. For reconstruction of the transmitted symbols phase shift elimination and amplitude optimisation is achieved by multiplication of the signal with
20 the complex-conjugate path weight $c_k^{(i)*}$. This reconstruction yields an enhancement of the strong signal paths and an additional weakening of already weak signal paths. After this reconstruction the signals of all fingers are added up in a combiner (not shown).

25

Furthermore, the signal is fed from the digital interpolator decimator 16 to N code-tracking loops, where exemplary the code-tracking loops of finger 1, finger 2 and finger N are denoted 101, 201 and 301, respectively, as seen in Fig. 1.
30 Each of the N code-tracking loops includes a timing error detector (TED) which generates error signals that are substantially proportional to the remaining path delay error

in the signal. The timing error detector of the first code-tracking loop or first finger is denoted 102. The error signals are lowpass-filtered in a loop filter to yield estimates for the respective path delay, again for each
5 finger, which are then fed back to a respective input of the interpolator/decimator 16, closing the tracking loop.

A conventional coherent early-late timing error detector 102' embedded in a code-tracking loop for one of the fingers i of
10 a rake receiver is depicted in Fig. 2. The timing error detector and other components downstream of the digital interpolator/decimator 16 is replicated for each rake finger $i \in \{1, 2, \dots, N\}$, whereas the interpolator/decimator 16 is used jointly. The samples $z(t = n \cdot T_c)$ 15 of the incoming signal are interpolated and decimated at the estimated timing delay $\hat{\tau}^{(i)}$ for the respective signal path assigned to the finger i . A first and second data streams are generated, the first stream is fed to the detection stream or path, more specifically to a correlator 120. It is noted that the
20 detection stream is not shown in full detail. The second data stream is fed to the synchronisation stream or path, more specifically to a correlator 121 and a shifter component (z^{-1}) 123. In the first stream the samples $z(t = k \cdot T_c + \hat{\tau})$ 110 are correlated with the pseudo-noise code 112 in the correlator
25 120. In the second or synchronisation stream shifted samples $z(t = k \cdot T_c - T_c/2 + \hat{\tau})$ 111, spaced by $-T_c/2$ with respect to the samples in the detection stream, are correlated with the pseudo-noise code in the correlator 121. Shifted samples 111 are further shifted by $+T_c$ in the component 123 to feed
30 samples $z(t = k \cdot T_c + T_c/2 + \hat{\tau})$ in the correlator 122. The two correlators 121, 122 of the synchronisation stream yielding early and late estimates 114, 113 of the transmitted symbols.

Estimates 113, 114 are substantially raised-cosine functions. If synchronisation of the samples is perfect, i.e. estimated time delay $\hat{\tau}$ is close to the real delay of the respective signal path, early and late estimates are spaced by $\pm T_c/2$ from the maximum of said raised-cosine function, respectively, and the difference of early and late estimates provided in step 124 is close to zero. When estimated delay $\hat{\tau}$ moves away from the real delay, difference of early and late estimates become finite yielding a delay compensation in the digital interpolator/estimator. Thus the tracking loop provides a synchronisation or locking loop for the digital signal. According to a next step 125 the difference signal 117 is multiplied with reconstructed transmitted symbols 115. Reconstructed transmitted symbols 115 are generated by complex-conjugately multiplying pilot symbols, e.g. of training sequences or symbol decisions with estimates of the channel phase or the channel phasor, but other methods of symbol reconstruction can also be applied. The real part of the resulting samples is extracted by circuit 126, now on symbol rate $1/T$, as error signal \tilde{x} 118. Error signal 118 is fed through the loop filter 103 with lowpass characteristic to yield the estimate for the timing delay $\hat{\tau}^{(i)}$. The general method of timing error detection is known in the art and e.g. described in Heinrich Meyr, Marc Moeneclaey and Stefan Fechtel, Digital Communication Receivers: Synchronization, Channel Estimation and Signal Processing, John Wiley and Sons, New York, 1998, A.J. Viterbi, CDMA - Principles of Spread Spectrum Communication, Addison-Wesley Publishing Company, Reading (MA), 1995, A. Wilde, Extended tracking range delay-locked loop, Proceedings of the International Conference on Communications, Seattle, USA, 1995 and Volker Aue and Gerhard P. Fettweis, A Non-Coherent Tracking Scheme

for the RAKE Receiver That Can Cope With Unresolvable
Multipath, Proceedings of the International Conference on
Communications, Vancouver, Canada, 1999.

Herewith, said documents are incorporated as subject matter
5 of the present disclosure by reference.

Fig. 3 shows one of the identical receiver fingers with an
early-late timing error detector 102 with adaptive
interference reduction at symbol rate according to the
10 invention, embedded in a code-tracking loop for one of the
fingers i in the rake receiver 17. Ideally interference is
nearly cancelled as result of signal subtraction 130 in an
interference reduction device 131. The chiprate processing
part is equivalent to that of the conventional timing error
15 detector 102' shown in Fig. 2.

According to the present invention the error signal coming
out of the timing error detector 102 and going into the loop
filter 103, is modified in the inventive timing error
20 detector adaptively by computing the interference from
adjacent multipaths. After multiplication of the
reconstructed symbols in the current finger i according to
step 125, interference from other fingers j ($j \neq i$) is
subtracted in step 130 from an intermediate signal 116 on
25 symbol rate $1/T$. For computing the interference channel state
information such as path amplitudes and phases as well as
path locations (relative to the current path i) are used. The
path locations are inherently available from the tracking
loops of the other rake fingers j ($j \neq i$), while the path
30 amplitudes and the phases can be derived from the channel
tracking units (not shown) of the other fingers.

As an alternative to interpolating and decimating the data signal 15 for each rake finger, the pseudo-noise code 112 can also be shifted in order to guarantee the correct alignment between data samples and pseudo-noise code samples.

- 5 Furthermore, due to normally very slowly varying path delays, delay tracking of all fingers can be implemented in time-sharing using only one dedicated tracking structure in an alternative embodiment of the invention.

- 10 A typical detector characteristic for the conventional coherent timing error detector, also called S-curve, is depicted in Fig. 4. The S-curve depends on the pulse filter used in the transmitter and the corresponding matched filter 12 in the receiver. Fig. 4 shows the expected value of the
- 15 error signal $x^{(i)}$ for an additive white gaussian noise channel and a raised-cosine pulse-matched filter autocorrelation function. The current path and as such the current rake finger is denoted by index i or exponent (i) . In a multipath environment, the timing error detection is influenced by
- 20 adjacent multipaths lying everywhere but in the zero-crossings of the S-curve. As an example, Fig. 5 further shows an S-curve of a second path j , causing a weaker signal component than path i and being time-shifted approximately by one chip duration T_c with respect to path i . It is clearly
- 25 seen that at the usual location of operation of the tracking loop for finger i which is the origin in the diagram, an additive interference from finger j will degrade the performance of the timing error detection. The interference depends on the distance of the two paths i and j , on the
- 30 instantaneous amplitude and also on the phase relation.

If the current channel conditions are known, either perfect

or by means of estimates, i.e. path amplitudes and phases as well as path delays are known, the interference from other fingers are estimated and subtracted from the timing error signal of the current finger. The rake receiver has a total of N fingers, and complex instantaneous channel tap phasors, which include amplitude and phase information, are denoted by the complex vector $c_k = [c_k^{(1)} \dots c_k^{(N)}]$. Furthermore, the path delays are given by $\tau = [\tau_k^{(1)} \dots \tau_k^{(N)}]$, where index k defines the current symbol for the path delays and the phasors.

The advantages of the inventive timing error detection will be clear from Fig. 4 and 5 representing the expected value of the error signal $E[x]$ for a non interfered path i (Fig. 4) and exemplary for another scenario where two paths i and j are interfering each other (Fig. 5). As shown in Fig. 4 the S-Curve is a function of the path delay τ , therefore, shall be denoted by $S(\tau)$ and is determined by the structure of the early-late timing error detector. On the x- and y-axis the timing delay τ in units of T_c and the expected value $E[x]$ are plotted, respectively. As long as the path i is not interfered the conventional timing error detector is unbiased, i.e. the value of the S-curve at the origin is zero, as shown in Fig. 4. Fig. 5 depicts the signal components for two different signal paths i and j , where the amplitude of component j is lower than the one of component i . The timing error detector for finger i is now biased, meaning that the superimposed contribution from path j results in a nonzero value of the S-curve for finger i at the origin. In advantageous contrast to that the timing error detector for finger i according to the invention subtracts interference of path j from the signal component of path i

such that reliable and stable path delay estimation and tracking in the tracking loop is provided for each signal component.

- 5 To provide the above described interference reduction the S-curve of the transmission system is stored in an interference computation module 132 being part of the interference reduction device 131. The interference computation module 132 receives the path delays 133 $\hat{\tau}_k^{(i)}$ and $\hat{\tau}_k^{(j)}$ for the assigned
10 signal path i and for all other paths $j \neq i$, respectively. Further, module 132 receives the complex path weights $c_k^{(j)}$ 134 of all other paths $j \neq i$ than the assigned signal path i .

In particular, for path i , the interference estimates of all
15 other fingers are subtracted from the intermediate signal $y_k^{(i)}$ 116 according to

$$\tilde{x}_k^{(i)} = \operatorname{Re}\{y_k^{(i)} - \sum_{j=1, j \neq i}^M c_k^{(i)*} c_k^{(j)} S(\hat{\tau}_k^{(i)} - \hat{\tau}_k^{(j)})\} \quad (1)$$

- 20 The first factor $c_k^{(i)*}$ accounts for the complex-conjugate of the maximum ratio coefficient used in finger i . The second factor $c_k^{(j)}$ stands for the channel tap phasor which the interfering path is subject to on the channel itself. The product of both is the total weight the interfering path is
25 subject to in finger i , and multiplied with the S-curve at the estimated correct location, $\hat{\tau}_k^{(i)} - \hat{\tau}_k^{(j)}$, it results in the interference contribution of finger j to finger i . The storage of S in the module 132 may be either by means of a mathematical function (e.g. an approximation by $\sin(\tau)/\tau$)

such that $S(\hat{\tau}_k^{(i)} - \hat{\tau}_k^{(j)})$ is calculated for each argument or S is stored by means of a look-up table such that the values of the function S are interpolated from the table values.

- 5 In the exemplary embodiment depicted in Fig. 1 and 3 the inventive timing error detection is applied for all receiver fingers $i \in \{1, 2, \dots, N\}$. Thus the invention yields for each finger i an interference cancelled or at least reduced error signal $\tilde{x}_k^{(i)}$ 118 and an interference reduced estimated timing delay $\hat{\tau}_k^{(i)}$ after the loop filter 103. Therefore, a significantly improved tracking is provided for all paths compared to prior art.

15 In another preferred embodiment, shown in Fig. 6, the real part of the intermediate signal $y_k^{(i)}$ 116 is extracted before reducing the interference. For this embodiment interference computation 132' is simplified by computing only the real part of the sum in Eq. (1) and it becomes

$$\tilde{x}_k^{(i)} = x_k^{(i)} - \sum_{j=1, j \neq i}^M \operatorname{Re}\{c_k^{(i)*} c_k^{(j)}\} S(\hat{\tau}_k^{(i)} - \hat{\tau}_k^{(j)}) \quad (2)$$

20

Figure 7 shows an alternative early-late structure, where the order of correlation and subtraction has been reversed. This is allowable due to the linear nature of the correlation operation and yields a simplified structure with only one correlator 121'.

25

Claims

1. A method for code-tracking in CDMA communication systems comprising
 - 5 a) receiving of an electromagnetic signal (10) being a superposition of a plurality of signal components of different signal paths (i),
 - b) digitising (14) the received signal (10, 13),
 - c) distributing the digitised signal (15) to receiver
10 fingers (1, 2, ..., N) each of which is assigned to one of the signal paths,
 - d) distributing the digitised signal (110, 111) to a detection stream and a synchronising stream,
 - e) decorrelating (121, 122) the digitised signal by a
15 code sequence (112) in the synchronisation stream and
 - f) reducing the interference of at least one other ($j \neq i$) than the signal component of the assigned signal path (i) with the signal component of the assigned signal path (i) in at least one of the
20 receiver fingers.
2. A method according to claim 1, wherein step f) comprises a subtraction (130) of an interference signal from the decorrelated digitised signal (116).
25
3. A method according to claim 1 or 2, wherein the subtraction takes place on symbol rate ($1/T$).
4. A method according to one of the preceding claims,
30 wherein interference of other signal components ($j \neq i$) than the assigned signal component (i) is reduced in all receiver fingers (1, 2, ..., N).

5. A method according to one of the preceding claims,
wherein step e) comprises decorrelating (121, 122) the
digitised signal by multiplying the digitised signal with
a complex-conjugate pseudo-noise code sequence (112).
6. A method according to one of the preceding claims,
wherein an early-late timing error detection (102) is
provided in the synchronisation stream.
7. A method according to one of the preceding claims,
wherein after step f) the real part (118, \tilde{x}) of the
interference reduced complex signal (\tilde{y}) is determined
(126).
8. A method according to one of claims 1 to 6, wherein
before step f) the real part (x) of the complex signal
(116, y) is determined (126).
9. A method according to one of the preceding claims,
wherein after step f) the interference reduced signal
(118, \tilde{x}) is filtered (103) in a step g).
10. A method according to claim 9, wherein
steps e), f) and g) provide a code-tracking (101) of the
digitised signal (111).
11. A method according to claim 10, wherein
the code-tracking (101) provides an estimated timing
delay ($\hat{\tau}^{(i)}$) of the signal component of the assigned
signal path (i).

12. A method according to one of the preceding claims,
wherein prior to step f) the digitised signal (111) is
distributed to a first and second correlator (121, 122).
- 5 13. A method according to claim 12, wherein
the digitised signal (111) is time-shifted prior to
feeding it to the second correlator (122) providing late
and early estimates (113, 114) as output of the first and
second correlator (121, 122), respectively.
- 10 14. A method according to claim 13, wherein
the early and late estimates (114, 113) are subtracted
(124) yielding an intermediate signal (117).
- 15 15. A method according to claim 14, wherein the intermediate
signal (117) is multiplied (125) with reconstructed
transmitted symbols (115).
- 20 16. A rake receiver (17) for processing a received
electromagnetic signal (10) being a superposition of
signal components of different signal paths, comprising
a plurality of receiver fingers (1, 2, ..., N),
wherein at least one of the receiver fingers (1, 2, ...,
N) is adapted to receive a signal component assigned to
25 one of the signal paths (i) with $i \in \{1, \dots, N\}$
a timing error detector (102) for estimating an error
of a delay ($\hat{\tau}_i^{(i)}$) of the signal component of the assigned
signal path (i) and
an interference reduction device (131) adapted to
30 reduce the interference of at least one other signal
component (j) with $j \neq i$ and $j \in \{1, \dots, N\}$ with the said
signal component of the assigned signal path (i).

17. A rake receiver (17) according to claim 16, wherein the interference reduction device (131) comprises an interference computation module (132) being adapted to receive complex path weights ($c_k^{(j)}$, 134) and path delays ($\hat{\tau}_k^{(i)}$, $\hat{\tau}_k^{(j)}$) to compute an interference signal of at least one other signal component (j) with the said signal component of the assigned signal path (i).
18. A rake receiver (17) according to claim 16 or 17, wherein the interference reduction device (131) is adapted to subtract (130) the interference signal of at least one other signal component (j) from the said signal component of the assigned signal path (i).
19. A rake receiver (17) according to one of the preceding device claims, comprising an A/D-converter (14) upstream of the receiver fingers (1, 2, ..., N), for digitising the received signal (10, 13).
20. A rake receiver (17) according to one of the preceding device claims, wherein the timing error detector (102) comprises an early-late gate timing error detector.
21. A rake receiver (17) according to one of the preceding device claims, wherein each receiver finger (1, 2, ..., N) comprises a loop filter (103).
22. A rake receiver (17) according to claim 21, wherein each receiver finger (1, 2, ..., N) comprises a code-tracking loop (101) comprising the timing error detector (102) and the loop filter (103).

14-01-2000

21

23. A rake receiver (17) according to claim 22, wherein
the code-tracking loop (101) is adapted to estimate a
timing delay ($\hat{\tau}^{(i)}$) of the signal component of the
5 assigned signal path (i).
24. A rake receiver (17) according to one of the preceding
device claims, wherein the timing error detector (102) is
adapted to provide pseudo-noise (112) decorrelation
10 (121, 122).
25. A rake receiver (17) according to one of the preceding
device claims, which is adapted for direct-sequence code-
division multiple access communication.

This Page Blank (uspto)

Abstract

The invention relates to a code-tracking method and a rake receiver for CDMA communication systems of low complexity yielding stable tracking. Received signal are distributed to a plurality of receiver fingers of a rake receiver. Each receiver finger i is assigned to a signal path of the transmitted signal which is subject to phase shift and power dissipation due to reflection, diffraction and scattering.


5 According to the invention in each receiver finger i an estimation of the timing delay $\hat{\tau}^{(i)}$ is provided and interference from other signal components j are subtracted from signal components of the current signal path i ($i \neq j$) yielding a reliable estimated timing delay $\hat{\tau}$.

10

This Page Blank (uspto)


(1-6)

Fig. 1



(2-6)

Fig. 2



14-01-2000

(3-6)




Fig. 3

Fig. 4






Fig. 5



(5-6)

Fig. 6



(6-6)

Fig. 7

